

Product Datasheet



734r 4 Channel Door Contact

The 734rEUR-00 and -01 transmitters are designed to work with any Scantronic 868MHz narrow band receiver. Both variants are two zone multi-function transmitters designed for use in any of the following applications:

- a) On their own as door contacts, using the supplied magnet.
- b) With a suitable external sensor to signal the opening of roller shutters by a set amount (-00 version only).
- c) With an external shock sensor to signal the presence of vibrations above a programmed level (-00 version only).
- d) With any voltage free contacts.

When used with both internal reed switch and external sensors the transmitter takes up two zones (or channels) on the receiver.

The external connector on the -00 variant is designed for four wire closed circuit sensors. The -01 variant is designed for Fully Supervised Loop (FSL) sensors.

In both variants the case is protected by an internal back tamper switch and an internal lid tamper switch.

Technical Specifications

Part Number	734rEUR-00, 734rEUR-01
Power Supply (Battery)	3V CR2 Li/MnO2 battery
Battery Life	Approximately 14 months
Temperature Range	-10 to +55°C
Low Voltage Alarm	2.4V nominal
Environmental Class	I (Tested -10 to +55°C)
Security Grade	II
INCERT No	C0160194

Compatible Transmitters/Receivers

Scantronic Homelink 7510 32 zone radio alarm system
Scantronic 762rEUR-00 2-channel receiver
Scantronic 768rEUR-00 8-32 channel receiver